


Mapping: (Top View)





Substrate: 1.59mm ±0.18mm [0.0625" ±0.007"] per IPC 4101/21, silver surface finish.



Pins: material- Brass Alloy 360 1/2 hard; finish-0.25µm [10µ"] Au over 1.27µm [50µ"] Ni (min.).

Description: 3 lead trimpot to 4 pin Dip adaptor

 $\frac{\text{Tolerances:}}{\pm 0.03 \text{mm } [\pm 0.001"]}, \text{ PCB perimeters } \pm 0.13 \text{mm } [\pm 0.005"], \text{ PCB thicknesses } \pm 0.18 \text{mm } [\pm 0.007"], \text{ pitches (from true position)} \\ \pm 0.08 \text{mm } [\pm 0.003"], \text{ all other tolerances } \pm 0.13 \text{mm } [\pm 0.005"] \text{ unless stated otherwise.} \\ \text{Materials and specifications are subject to change without notice.}$

DC-TRIMPOT-3099-01 Drawing/Map	Status: Released	Scale	3:1	Rev: B
© 1999 IRONWOOD ELECTRONICS, INC. PO BOX 21151 ST. PAUL, MN 55121 Tele: (651) 452-8100 www.ironwoodelectronics.com	Drawing: W. Watson		Date: 11/23/99	
	File: DC-TRIMPOT-3099-01 Dwg		Modified: 10/17/05	